Zeta

پنل اعلام حريق

infinity8



MODEL	IN2	IN4	IN6	IN8	In12	
Part No	37-651	37-652	37-653	37-654	37-655	
Mains Voltage	230V AC +10% / -15% @ 50/60 Hz					
System Voltage	24V DC (Nominal)					
Zone Voltage	21V DC (N	21V DC (Nominal)				
Sounder Alarm Output	2 x 150mA	2 x 150mA @ 24V DC 4 x 150mA @ 24V DC				
Fault Relay	1 x Volt Fr	1 x Volt Free Relay, SELV @ 1A Max				
Fault Relay	1 x Volt Fr	1 x Volt Free Relay, SELV @ 1A Max				
Zone Capacity	32 devices per zone					
Remote sounder operation	Via N/O contact connected to Class Change					
Sounder Activation Delay	0 to 10 minutes in 1 minute increments					
Zone End of line	1N4002 Diode (Cathode Stripe to Zone +ve)					
Sounder End of Line	10K resistor					
Charger Voltage	27.6V					
Battery cut off	Battery voltage less than 20 V					
Battery Internal Resistance limit	0.9 ohm					
Enclosure size	375 x 316 x 90 (mm)					
Weight	3 kg (Exclu	3 kg (Excluding Batteries)				
Maximum battery space	2 x 3.4 Ah, 12 Vdc sealed lead acid					

