Zeta

# دتکتور گاز

## ZG-100

| MODEL | ZG-100N | ZG-100L |
|---|---|---|
| PART NO | 47-405 | 47-410 |
| SUPPLY VOLTAGE | 230V @50/60Hz AC or 9-28V DC | |
| QUIESCENT CURRENT | 140 mA | |
| START-UP CURRENT | 220mA | |
| ALARM CURRENT | 500mA (excluding Alarm output) | |
| BUZZER OUTPUT | 85dB@ 3m | |
| OPERATING TEMPERATURE | 0°C to 50°C | |
| MAX. HUMIDITY | 95% RH N/C | |
| RESPONSE TIME | <30 SECONDS | |
| SENSITIVITY | 4400ppm | 1700ppm |
| SIZE (WxHxD mm) | 150mm x 90mm x 70mm | |
| WEIGHT | 1 kg | |

PANTA

www.panta.ir TEL : 021-33996626